

Exhibit 2

CV53_25Nov05

ID	Feature
0	None
1	Horn
2	Std/Alt Horn Select
5	Dynamic Brakes
8	Motor Cooling Fans
9	Long Air Letoff
10	Short Air Letoff
64	Mute
65	Doppler
96	Directional Headlight
97	Directional Reverse Light
98	Headlight
99	Dim Headlight
100	Reverse Light
176	Air Brakes
178	Status Report
211	Coupler
215	Squealing Brakes
216	Flange/Air Brakes

Features that can be assigned to CV53.x.1

ID	Feature
0	None
1	Horn
2	Std/Alt Horn Select
5	Dynamic Brakes
8	Motor Cooling Fans
9	Long Air Letoff
10	Short Air Letoff
64	Mute
96	Directional Headlight
97	Directional Reverse Light
98	Headlight
99	Dim Headlight
100	Reverse Light
144	Startup
145	Discon/Standby/Shutdown
178	Status Report
211	Coupler
217	Air Pumps

Defaults

CV53.1.0 = 96	CV53.1.1 = 96
CV53.2.0 = 97	CV53.2.1 = 97
CV53.3.0 = 3	CV53.3.1 = 3
CV53.4.0 = 1	CV53.4.1 = 1
CV53.5.0 = 211	CV53.5.1 = 211
CV53.6.0 = 8	CV53.6.1 = 8
CV53.7.0 = 5	CV53.7.1 = 5
CV53.8.0 = 65	CV53.8.1 = 144
CV53.9.0 = 216	CV53.9.1 = 9
CV53.10.0 = 64	CV53.10.1 = 64
CV53.11.0 = 10	CV53.11.1 = 145
CV53.12.0 = 178	CV53.12.1 = 178
CV53.13.0 = 10	CV53.13.1 = 10
CV53.14.0 = 10	CV53.14.1 = 10

Model 200 GG1 (BLI)
CV53 Output Mappings

CV53_25Nov05

Features that can be assigned to CV53.x.0

ID	Feature
----	-----
0	None
1	Horn
3	Bell
5	Dynamic Brakes
8	Motor Cooling Fans
9	Long Air Letoff
10	Short Air Letoff
64	Mute
65	Doppler
96	Directional Headlight
97	Directional Reverse Light
98	Headlight
99	Dim Headlight
100	Reverse Light
176	Air Brakes
178	Status Report
211	Coupler
215	Squealing Brakes
216	Flange/Air Brakes

Features that can be assigned to CV53.x.1

ID	Feature
----	-----
0	None
1	Horn
3	Bell
5	Dynamic Brakes
8	Motor Cooling Fans
9	Long Air Letoff
10	Short Air Letoff
64	Mute
96	Directional Headlight
97	Directional Reverse Light
98	Headlight
99	Dim Headlight
100	Reverse Light
144	Startup
145	Discon/Standby/Shutdown
178	Status Report
211	Coupler
217	Air Pumps

Defaults

CV53.1.0 = 96	CV53.1.1 = 96
CV53.2.0 = 97	CV53.2.1 = 97
CV53.3.0 = 3	CV53.3.1 = 3
CV53.4.0 = 1	CV53.4.1 = 1
CV53.5.0 = 211	CV53.5.1 = 211
CV53.6.0 = 8	CV53.6.1 = 8
CV53.7.0 = 5	CV53.7.1 = 5
CV53.8.0 = 65	CV53.8.1 = 144
CV53.9.0 = 216	CV53.9.1 = 9
CV53.10.0 = 64	CV53.10.1 = 64
CV53.11.0 = 10	CV53.11.1 = 145
CV53.12.0 = 178	CV53.12.1 = 178
CV53.13.0 = 10	CV53.13.1 = 10
CV53.14.0 = 10	CV53.14.1 = 10
